

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-1 of 11

## Chapter 8.1 Electrical Safety

### ***This could be you . . .***

***During a late-night shift when no electrical technician was available, a mechanical technician was instructed to work on a live electrical panel in a test area. He was shocked by 480 volts, but received only minor burns to the thumb.***

***A worker suffered flash burns when his scraper was vaporized by high-voltage electricity while scraping a louvered duct for painting. The duct contained a power buss, and the scraper entered a louver and shorted the buss to the duct.***

#### **8.1.1 Applicability of this chapter**

You are required to follow the requirements in this chapter if you design, install, maintain, or work on electrical equipment or if your work exposes you to the hazards of electricity.

#### **8.1.2 What this chapter covers**

This chapter covers the minimum requirements for work on power generation, transmission, and distribution systems, motors, transformers, rectifiers, voltage regulators, batteries, battery chargers, and associated components. There are additional requirements for working with batteries in Chapter 6.1, "Battery Safety."

#### **8.1.3 Electrical safety program**

8.1.3.1 The following describes JSC's electrical safety program:

- a. Electrical safety program principles. JSC workers and organizations shall:
  - (1) Follow NFPA 70E, to include arc flash requirements.
  - (2) Inspect and evaluate electrical equipment. *This includes testing test equipment used before and after each test.*
  - (3) Maintain electrical equipment's insulation and enclosure integrity.
  - (4) Classify circuits operating at or above 600 volts nominal or 600 volts root mean square as SAFETY CRITICAL. Written procedures require approval from an electrical crew supervisor or contractor safety officer and the supervisor shall be present during operations.
- b. Electrical hazard controls. Electrical workers shall follow the general principles of hazard control in Chapter 3.2 and these specific electrical hazard controls:
  - (1) Consider every electrical conductor or circuit part to be energized until proven otherwise.
  - (2) Make no bare-hand contact with exposed energized electrical conductors or circuit parts operating at 50 volts or more, unless the bare-hand method is properly used.
  - (3) De-energize, if possible. Live parts operating at less than 50 volts to ground need not be de-energized if there will be no increased exposure to electrical burns or to explosion due to electric arcs.

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-2 of 11

- c. Written and approved procedures as described in NFPA 70E, Article 110 and Chapter 5.8, paragraph 5.8.13.
- d. Documented and approved hazard identification and risk assessment as described in NFPA 70E, Article 110 and Chapter 2.3.
- e. Job briefings as described in NFPA 70E, Article 110.
- f. Program audits every three years and random field audits as described in NFPA 70E, Article 110.

#### **8.1.4 Limitations for working on electrical equipment**

Electrical workers shall follow the limitations listed below:

<b><i>When you are . . .</i></b>	<b><i>You shall . . .</i></b>
Maintaining electrical equipment	<ul style="list-style-type: none"> <li>• Work only on de-energized equipment. (See lockout/tagout (LO/TO) in Chapter 8.2.)</li> <li>• Get an exception to this limitation from the appropriate authority by performing and documenting an investigation. Your company or directorate shall have policies for working on energized equipment clearly defining the “appropriate authority.” Only designated “qualified electricians” or “electronic technicians” may work on energized equipment. (See NFPA 70E, Article 130.)</li> <li>• Verify equipment cannot be re-energized by attempting a restart using the normal operating controls (where possible) to make sure the equipment or system will not operate. You may need to request a remote restart. (See LO/TO in Chapter 8.2.)</li> <li>• Make sure all covers, barriers, housings, and containment devices are in place.</li> </ul>
Doing maintenance, repair, or construction on overhead line or in a substation, where the wiring is congested and you are exposed to or must handle energized equipment	<ul style="list-style-type: none"> <li>• Have at least one additional employee who watches the other workers and warns them if they get near live conductors or helps them if there is an accident.</li> <li>• Have at least two CPR-qualified employees on site.</li> <li>• Assign enough qualified workers to perform the work safely as a supervisor.</li> </ul>
Doing potentially hazardous operations	<ul style="list-style-type: none"> <li>• Limit access to the work area to authorized personnel only.</li> </ul>

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-3 of 11

### 8.1.5 Controls for working safely on electrical equipment

Employees working on electrical equipment shall implement the following controls:

<b><i>If you are . . .</i></b>	<b><i>Then you shall. . .</i></b>
Doing an inspection or maintaining equipment	<ul style="list-style-type: none"> <li>• Be qualified to inspect and maintain the electrical equipment.</li> <li>• Inspect the equipment at predetermined intervals.</li> </ul>
Adjusting equipment	<ul style="list-style-type: none"> <li>• Never adjust any part of electrical or electronic equipment if there is a risk you can contact unprotected energized equipment.</li> <li>• Get approval from the electrical supervisor and the Safety and Test Operations Division if you must work on circuits at or over 50 Vac.</li> </ul>
Working around energized electrical circuits	<ul style="list-style-type: none"> <li>• Never wear rings, watches, neck chains, or other metallic objects that are electrical conductors.</li> <li>• Wear the proper personal protective equipment (PPE).</li> <li>• Work on energized equipment ONLY if you are a designated “qualified electrician” or “electronic technician.” (See NFPA 70E, Article 130.)</li> </ul>
Repairing or testing electronic equipment on a work bench	<ul style="list-style-type: none"> <li>• Keep work benches clean at all times.</li> <li>• Ground all metal work benches.</li> </ul>
Working on poles	<ul style="list-style-type: none"> <li>• Follow the requirements in 29 CFR 1910.268, “Telecommunications,” 29 CFR 1910.269, “Electric Power Generation, Transmission, and Distribution,” and 29 CFR 1926.950–960, “Power Transmission and Distribution.”</li> <li>• Inspect all poles before climbing them to do line work, and pike or support them before climbing if they are rotten or weak.</li> <li>• Use proper PPE, tools, and barriers to protect workers from energized circuits.</li> <li>• As a pole climber (lineman), firmly set your spurs and fasten your safety belt before working on pole-mounted electrical lines or equipment.</li> <li>• As the first of two linemen working on the same pole, be in the working position (safety belt fastened) before the second lineman climbs the pole.</li> <li>• Complete all work on one line or phase before working on another; never work on two lines or phases simultaneously when on a pole.</li> <li>• Never intentionally drop anything from a pole to the ground or allow anything to be tossed up to you.</li> <li>• Turn your head away to diminish the risk of injury from an arc blast when opening primary disconnects or cutouts.</li> <li>• Use certified connect/disconnect extension poles when possible.</li> </ul>
Working on micro-wave equipment	<ul style="list-style-type: none"> <li>• Know about radiation hazards before working on microwave equipment to avoid possible tissue injury, particularly to the eyes.</li> <li>• Never examine or adjust radiators, waveguide openings, or horns during transmission.</li> <li>• Post warning signs that follow 29 CFR 1910.97 if someone may inadvertently enter the path of a microwave beam greater than 10 mw/cm<sup>2</sup>.</li> </ul>

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-4 of 11

Grounding equipment	<ul style="list-style-type: none"> <li>Ground non-current-carrying metal parts exposed to contact by personnel with a continuous conductor from the device to a known good ground point.</li> <li>See NFPA 70, "National Electric Code," Article 250, "Grounding and Bonding," and OSHA 29 CFR 1910.302–308, Subpart S, "Electrical," for requirements.</li> <li>Ensure semi-portable equipment such as generators, electric hand tools, and floodlights are properly grounded.</li> <li>Maintain the protective ground on the metal enclosures during movement, unless the supply circuits are de-energized.</li> </ul>
Cleaning electronic equipment	<ul style="list-style-type: none"> <li>Use only approved and authorized solvents to clean electronic equipment.</li> <li>Provide adequate ventilation and PPE as directed in the Safety Data Sheet (SDS) for the solvent (see Part 9 for details on hazardous materials).</li> </ul>
Working on high-voltage systems	<ul style="list-style-type: none"> <li>Have at least two persons trained in CPR per work crew.</li> </ul>
Locking or tagging out equipment	<ul style="list-style-type: none"> <li>Follow the requirements of OSHA 29 CFR 1910.147, "The Control of Hazardous Energy (Lockout/Tagout)." (See LO/TO in Chapter 8.2.)</li> </ul>

### 8.1.6 Additional requirements for working safely with electrical equipment

Employees working with electrical equipment shall follow the regulations listed below:

<b><i>If you are . . .</i></b>	<b><i>Follow . . .</i></b>
Locking or tagging out an electrical energy source	Chapter 8.2, which implements OSHA 29 CFR 1910.147
Working on communications equipment	OSHA 29 CFR 1910.268
Working on high voltage transmission and distribution equipment	OSHA 29 CFR 1910.269
Working on common facility wiring and equipment	<ul style="list-style-type: none"> <li>OSHA 29 CFR 1910, Subpart S (all), "Electrical"</li> <li>NFPA 70 "National Electric Code" and 70E, "Standard for Electrical Safety in the Workplace."</li> </ul>

### 8.1.7 Safety design requirements for JSC electrical equipment

8.1.7.1 Permanent JSC electrical equipment shall meet the following requirements:

a. Electrical equipment shall have the following safety features:

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-5 of 11

<i>For . . .</i>	<i>You shall use equipment that . . .</i>
Equipment in ordinary occupancies	Is listed by UL, FM, or other recognized testing laboratories. Meets the design requirements of the project specification and of NFPA 70.
Equipment in hazardous locations	Meets the design requirements in NFPA 70, "National Electrical Code," especially Chapter 5, "Special Occupancies," and OSHA 29 CFR 1910.307, "Hazardous Locations."
Safety mechanisms	Meets the requirements listed in paragraph 8.1.6 above to ensure personnel and equipment safety.
Minimizing accidental contact	Is designed to locate or guard control boards, switches, transformers, and other hazardous equipment operating at 50 volts or more with grounded railings, barriers, or enclosures.  Has all sharp edges removed and/or isolated from electrical conductors.  Has sufficient room for wiring and maintenance.  Does not apply undue forces on electrical terminations.

- b. The equipment design documents shall show voltage, frequency, number of phases, type of raceways, type, number, and size of conductors, and all data pertinent to personnel and equipment safety.
- c. The Safety and Test Operations Division shall review electrical systems designs.
- d. Permanently tag wires, terminals, and equipment with identification numbers that agree with the associated wiring diagrams and schematics.

### **8.1.8 Grounding JSC electrical equipment**

8.1.8.1 Permanent JSC electrical equipment shall meet the following safety requirements for grounding:

- a. Follow NFPA 70, National Electric Code Article 250, and OSHA 29 CFR 1910.302–308.
- b. Show grounding points and grounding details on project drawings and diagrams.
- c. Protect the grounds from physical damage.
- d. Test newly installed grounding systems and document the tests.
- e. Provide an effective separate ground for non-current-carrying metal parts in:
  - (1) Generators, switches, or motor controller enclosures
  - (2) Fuse boxes, distribution cabinets, frames, tracks, and motors of electrically operated equipment

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-6 of 11

### 8.1.9 Electrical safety requirements for temporary JSC equipment

JSC temporary equipment shall meet the following requirements:

<b><i>For . . .</i></b>	<b><i>You shall . . .</i></b>
Temporary lines	<ul style="list-style-type: none"> <li>• Limit service to 90 days unless approved by the Safety and Test Operations Division.</li> <li>• Guard or elevate open wiring with 600 volts or less 10 feet above walkways to prevent accidental contact by workers who may be carrying construction materials or tools.</li> </ul>
Cords and connections	<ul style="list-style-type: none"> <li>• Use portable power tool cords having an identified grounding conductor connected to the frame or are double-insulated with a UL label.</li> <li>• Use cords connected to the grounding contact of an approved plug and UL-listed for the intended use.</li> <li>• Use an appropriately sized ground fault circuit interrupter (GFCI) near the power source on temporary circuits that power tools.</li> <li>• Ensure extension cords are large enough for the load and are sized to minimize the voltage drop.</li> </ul>
Temporary wiring in tanks or confined spaces	<ul style="list-style-type: none"> <li>• Provide a properly identified FM- or UL-listed switch, which is rated for the environment, at or near the entrance to allow for Emergency Power Shut-Down.</li> <li>• Protect all circuits with GFCIs.</li> </ul>

### 8.1.10 Installing and servicing transformers

8.1.10.1 Employees who install or service transformers shall:

- Control access to ground-level outdoor transformers by meeting the requirements in paragraph 3.6.1 of NPR 8715.3.
- Provide for the safe removal of oil spilled during routine maintenance around all outdoor transformers.
- Make sure transformers do not contain any traceable amounts of polychlorinated biphenyls (PCBs).
- Test for PCBs. If you suspect them, take all precautions as if they were present (see Chapter 9.1, "Hazardous Materials Safety and Health"). Contact the Safety and Test Operations Division or Occupational Health for additional information and instructions.
- Never place liquid-filled transformers indoors without permission from the Center Operations Directorate.

### 8.1.11 Requirements for installing lighting systems

Lighting systems shall meet NFPA 70.

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-7 of 11

### **8.1.12 Features to include when designing an emergency lighting or power system**

8.1.12.1 Emergency lighting or power systems shall follow NFPA 101, National Electric Code Article 700, and the requirements listed below:

- a. Provide an independent source of energy to light work areas, corridors, tunnels, exits, and stairways during a power failure.
- b. Provide a visual alarm system to warn of improper operation.
- c. Never use circuits or outlets powering emergency lighting chargers for other lights or appliances.
- d. Make sure emergency lights automatically activate when the primary lighting system fails or during a power failure. A failure of any one component in the emergency system shall never leave any critical space in total darkness.
- e. Make sure emergency power circuits have an emergency supply source to which the load will be switched automatically when the primary source fails.
- f. Provide a switch for testing the emergency lighting system. The test switch shall be clearly marked and accessible from the normal working level.
- g. Make sure generators used to supply emergency power are started, brought up to speed and frequency, and put on line as soon as emergency switching operations can be done safely.

### **8.1.13 Requirements for operating emergency power and lighting systems**

8.1.13.1 Employees operating emergency power or lighting systems shall follow NASA-STD-8719.11 and the requirements listed below:

- a. Put multipurpose dry chemical or CO<sub>2</sub> extinguishers next to generators.
- b. Store generator fuels in approved containers in a protected location when storing reserve fuel for a mobile power source.
- c. Refuel generators using approved containers and fuel dispensers.
- d. As the immediate supervisor, you shall make sure:
  - (1) Servicing, operating, or maintaining of emergency power equipment is performed by qualified and certified personnel.
  - (2) The maintenance crew is proficient in administering CPR, familiar with pertinent safety regulations, and supplied with appropriate safety equipment.
- e. Use approved plans to do maintenance on emergency lighting and power systems.
- f. Have the Electrical Operations Branch, Plant Engineering Division, approve repairs on or modifications to emergency lighting and power systems.
- g. Ground portable generators per NFPA 70 Article 250 and manufacturer's instructions.



<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-8 of 11

#### **8.1.14 Defective electrical equipment**

8.1.14.1 Remove power from defective electrical equipment immediately. If the equipment could cause personal injury and cannot be repaired immediately, attach **WARNING - DO NOT OPERATE** tags, JSC Form 19A (Appendix D). (Note: JSC Form 19A is different than JSC Form 1291, the "Danger, Lockout/Tagout (Tag).") Electrical equipment with the following defects requires tags:

- a. Poor ground impedance.
- b. Energized ground wires.
- c. Exposed wiring.
- d. Loose receptacle housings.
- e. Broken receptacles.
- f. Reversed polarity in shop areas.
- g. Failure to function unless the cause is known to be nonhazardous.

#### **8.1.15 Removing a *DANGER*, *CAUTION*, and *WARNING* tag or sticker**

Normally, only the installer is allowed to remove a danger, caution, or warning tag. However, when defective electrical outlets are repaired, the repair electrician may remove the tag or sticker and shall notify the person who attached it and the facility manager.

#### **8.1.16 Preventing hazardous static discharges**

8.1.16.1 Employees shall:

- a. Bond and ground all systems designed to transfer, store, or handle flammable gases or liquids.
- b. Use inductive floors or other methods to prevent discharge where it is a significant hazard.

#### **8.1.17 Specific design and installation requirements for bonding and grounding these systems**

Employees shall follow the requirements listed below to bond and ground systems mentioned in paragraph 8.1.16:

Note: These installations shall be individually engineered to meet the codes for the various products and environmental conditions.



<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-9 of 11

<b><i>If you are working with . . .</i></b>	<b><i>Then you shall . . .</i></b>
Flammable gases or liquids	<ul style="list-style-type: none"> <li>Follow the engineering specifications, and all local and national codes.</li> <li>Use a correctly sized bond or ground wire with adequate strength, corrosion resistance, and flexibility for the service intended. You may use insulated or non-insulated wire.</li> <li>Follow NFPA 77, "Static Electricity," for the design of ground systems unless the NASA design standards are more restrictive.</li> </ul>
Storage tanks, equipment, and piping	<ul style="list-style-type: none"> <li>Follow the engineering specifications, and all local and national codes.</li> <li>Ground per the engineering design drawings, which will take into consideration the stored material.</li> <li>Make sure the resistance of the tank, piping, or equipment to ground meets the design specifications.</li> <li>Install provisions for grounding all components, including the tank car or tank truck. The system may have to be the alarming type. Check the engineering specifications.</li> </ul>
Submerged filling lines	<ul style="list-style-type: none"> <li>Follow the engineering specifications, and all local and national codes.</li> </ul>
Grounding or bonding connections	<ul style="list-style-type: none"> <li>Follow the engineering specifications, and all local and national codes.</li> </ul>

### **8.1.18 Specific operational requirements for bonding and grounding temporary storage vessels**

Employees shall ground transport vessels, portable containers, and other types of temporary storage vessels while transferring flammable liquids or gases. Visually check the grounding and bonding system before each transfer operation to make sure all connections are good and there is a continuous path to ground. Periodically check the grounding system with the appropriate test equipment.

### **8.1.19 Hazards of static discharges**

8.1.19.1 Static discharge could cause serious injury by the following hazards:

- An explosion could occur in a flammable atmosphere caused by a spark from a charged object near a ground line or another charged object.
- A large enough static discharge could set off igniter circuits.
- Although static electricity is not lethal, your reaction to a shock may be enough to cause injury or cause damage to equipment.

### **8.1.20 Precautions for reconnecting or restarting critical equipment after an electrical maintenance or a power outage**

Verify correct voltage, phase, polarity, and current-limiting devices (including motor overloads). Contact Facility Management and the Operations Office for help.

### **8.1.21 Training for working on electrical equipment**

Verify correct version before use at [Center Directives Management System](#).  
JSC Form JF2420B (Revised April 3, 2012) (MS Word August 28, 2006)

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-10 of 11

8.1.21.1 Electricians shall be trained and certified as follows:

- a. As described in NFPA 70E, Article 110.
- b. To install, maintain, and operate electrical equipment and power lines.
- c. LO/TO training described in Chapter 8.2.
- d. In electrical safe work practices, emergency procedures, first aid, and CPR before maintaining electrical equipment or working with exposed energized circuits. This includes periodic refresher training.
- e. To work on energized equipment.
- f. To work on high-voltage systems
- g. In Hazardous Operations Procedure requirements as described in Chapter 5.8.

Note: See Chapters 4.1, "Safety and Health Training", and 5.8, "Hazardous Operations: Safe Practice and Certification," for more requirements on training and certification.

### 8.1.22 PPE for electrical work

Electrical workers shall follow these requirements for PPE and use any other PPE identified in a Job Hazard Analysis. See Chapter 5.6, "Personal Protective Equipment," for more requirements on PPE:

<b><i>For . . .</i></b>	<b><i>You shall . . .</i></b>
All PPE	<ul style="list-style-type: none"> <li>Inspect PPE before each use to make sure the insulating qualities provide adequate protection.</li> </ul>
Electrically insulating rubber equipment	<ul style="list-style-type: none"> <li>Use equipment classified and marked Class 0-4, and meets the design requirements of OSHA 29 CFR 1910.137(a), "Electrical Protective Devices."</li> <li>Inspect and test equipment to meet the requirements of OSHA 29 CFR 1910.137(b).</li> </ul>
Safety gloves	<ul style="list-style-type: none"> <li>Use gloves designed for electrical work and inspect them for cuts, punctures, or signs of wear before beginning work.</li> <li>Never use gloves with an insulation rating less than the working voltage.</li> <li>Wear leather gloves over safety gloves to avoid cutting or tearing them.</li> <li>Make sure the gloves have been inspected and tested at least every 6 months as described in OSHA 29 CFR 1910.137(b).</li> </ul>
Lineman's spurs	<ul style="list-style-type: none"> <li>Use spurs at least 1¼-inch long.</li> <li>Make sure they have safety covers to cover the gaffs when not in use.</li> </ul>
Safety belts	<ul style="list-style-type: none"> <li>Use belts for climbing over 4 feet above the ground (see Chapter 8.8 for specific requirements).</li> </ul>
Ladders	<ul style="list-style-type: none"> <li>Use nonconductive ladders meeting OSHA 29 CFR 1910.25, "Portable Wood Ladders," OSHA 29 CFR 1910.268(H), OSHA 29 CFR 1910.269-1(H), and ANSI standards if doing maintenance on or near electrical</li> </ul>

<b>JSC Safety and Health Requirements</b>	JPR No.	<b>1700.1L</b>
	Effective Date:	<b>12/20/2018</b>
	Expiration Date:	<b>12/20/2023</b>
	Page Number	Page 8.1-11 of 11

	equipment (see Chapter 8.7, "Ladders, Scaffolds, and Elevated Platforms: How to Work with Them Safely," for specific requirements).
Working on energized systems.	<ul style="list-style-type: none"> <li>Refer to NFPA 70E, Article 130, for the requirements.</li> </ul>

### 8.1.23 Electrical emergencies

8.1.23.1 Employees shall take the following actions for these emergency situations:

a. For *electrical shock*:

- (1) Call for help using the emergency phone numbers or using a two-way radio.
- (2) Switch the power off.
- (3) Administer first aid and, if necessary, CPR.
- (4) Do not attempt to separate the energized circuit from the victim.

b. For a *fire*:

- (1) Evacuate the area.
- (2) Call for help using the emergency phone numbers or using a two-way radio.
- (3) Use a CO<sub>2</sub> or multipurpose dry chemical extinguisher to fight only the incipient fire, and only if trained to use an extinguisher properly. See Chapter 3.8, "Emergency Preparedness."

Remember your emergency number: x33333 or (281) 483-3333 at JSC, Sonny Carter Training Facility, and Ellington Field, 911 at any off-site location, and x5911 at WSTF.

### 8.1.24 Responsibilities

a. As an **electrical supervisor**, you are responsible for making sure:

- (1) An LO/TO program is in place and is being used correctly.
- (2) All electrically powered tools are in good working condition.
- (3) All safety devices are available, maintained, and properly used.
- (4) All assigned personnel follow safety requirements.
- (5) Electrical work is done by employees trained and certified for the task or the employees are under the direct supervision of a trained and certified person.

b. The **Safety and Test Operations Division** is responsible for auditing JSC's electrical safety program as described in subparagraph 8.1.3.1.f.